

Fiber Optical Transmitter

1 - 2500MHz, Analog/Digital, RF-over-Fiber Tx/Rx Pair with RF Fiber Break



DATASHEET

[Return to the Webpage](#)



Features

- Excellent Linearity and Flatness
- 45 -1000MHz Working Bandwidth
- Wide Range of Optical Input Power
- Single-Mode Fiber
- Ultra Low Noise Technology
- Smaller Size and Easy to Install
- Built-In Filter
- Low Power Loss Design

Applications

- FTTH (Fiber To The Home) Networks



Note: The specifications provided are for general applications with a cost-effective approach. If you need to narrow or expand the tolerance, coverage, limit, or qualifications, please [click this link](#):

Rev 03/16/26

The RFOF Transmitter (Tx) and Receiver (Rx) pair is engineered to transmit analog or digital RF signals over optical fiber, providing a secure and reliable link between two short-distance locations. Designed for high-security applications, this system ensures low-loss, high-fidelity signal transport while maintaining signal integrity. An optional RF Fiber Break configuration is available, enabling unidirectional RF transmission over a single fiber link. This feature prevents signals from being passed in the return direction, ensuring one-way communication for enhanced security and isolation, often required in military and critical infrastructure applications. This series of RFOF links covers a wide frequency range from 5 MHz to 2.5 GHz, featuring an exceptionally flat frequency response for both analog and digital signals. The system is designed for plug-and-play operation, with compact units that include a wall pluggable power supply for easy deployment and minimal setup time.

Specifications (Transmitter)

Parameter	Min	Typical	Max	Unit
Wavelength	1310 $\pm$ 20, 1550 $\pm$ 20			nm
Frequency range	1		2500	MHz
RF input level	72		82	dBuV
Flatness in band		± 0.75		dB
Rf input resistance		75		ohm
Input reflection loss		≥ 16		dB
Link C/N		≥ 51		dB
Link C/CSO		≥ 60		dB
Link C/CTB		≥ 65		dB
AGC controlling range		± 5		dB
MGC controlling	0		10	dB
Laser type	DFB laser			
Optical connector type	SC/APC			
Power Supply	DC 12 V/1 A			
Power Consumption	≤ 4			W

P +1 781-935-1200

E sales@agiltron.com

W www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice.
Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.

Fiber Optical Transmitter

1 - 2500MHz, Analog/Digital, RF-over-Fiber Tx/Rx Pair with RF Fiber Break



 DATASHEET |

Mechanical Dimensions (mm)

*Product dimensions may change without notice. This is sometimes required for non-standard specifications.

 +1 781-935-1200

 sales@agiltron.com

 www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice.
Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.

Fiber Optical Transmitter

1 - 2500MHz, Analog/Digital, RF-over-Fiber Tx/Rx Pair with RF Fiber Break



DATASHEET |

Transmitter: Bias Switch Selection Table

Item	Switch 1	Switch 2	LED 1	LED 2
13V / 0Hz	OFF	OFF	Red	Red
18V / 0Hz	ON	OFF	Green	Red
13V / 22kHz	OFF	ON	Red	Green
18V / 22kHz	ON	ON	Green	Green

+1 781-935-1200

sales@agiltron.com

www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice.
Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.

Fiber Optical Transmitter

1 - 2500MHz, Analog/Digital, RF-over-Fiber Tx/Rx Pair with RF Fiber Break



DATASHEET

Ordering Information (Part Number)

Prefix	RF Frequency	Wavelength	TX/RX	Package	Directional ^[1]	RF Fiber Breaker	Fiber Connector ^[2]
RFOF-	2.5GHz = 025 1GHz = 010 Special = 000	1550 nm = 1 1310 nm = 3 1490 nm = 4 Special = 0	Receiver = 1 Transmitter = 2 Receiver + Transmitter = 3	Module = 1 Rack = 2 Special = 0	Monodirectional = 1 Bidirectional = 2	Non = 1 Yes = 2	FC/APC = 2 FC/UPC = 3 SC/UPC = 4 LC/APC = A LC/UPC = U Special = 0

Note:

- [1]. Bidirectional means two-way communications via a single fiber link. The price is double since it comprises two pairs of transceivers and receivers with WDM (different wavelength) or circulator (same wavelength) cable jumpers.
- [2]. The default connector configuration uses fiber with 0.9 mm buffer protection. The connector cannot be installed directly onto bare fiber because the bare fiber is prone to damage during shipping. However, the connector can be assembled on bare fiber if a 3 cm protective loose tube is added for reinforcement. The customer may remove this protective tube after testing. The optical power handling of a standard connector is less than 0.5 W for SMF-28 fiber and decreases further for smaller-core fibers.

Red marked -- Special order

Application Notes

Fiber Core Alignment

Note that the minimum attenuation for these devices depends on excellent core-to-core alignment when the connectors are mated. This is crucial for shorter wavelengths with smaller fiber core diameters that can increase the loss of many decibels above the specification if they are not perfectly aligned. Different vendors' connectors may not mate well with each other, especially for angled APC.

Fiber Cleanliness

Fibers with smaller core diameters (<5 µm) must be kept extremely clean, contamination at fiber-fiber interfaces, combined with the high optical power density, can lead to significant optical damage. This type of damage usually requires re-polishing or replacement of the connector.

Maximum Optical Input Power

Due to their small fiber core diameters for short wavelength and high photon energies, the damage thresholds for device is substantially reduced than the common 1550nm fiber. To avoid damage to the exposed fiber end faces and internal components, the optical input power should never exceed 20 mW for wavelengths shorter 650nm. We produce a special version to increase the how handling by expanding the core side at the fiber ends.

+1 781-935-1200

sales@agiltron.com

www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice.
Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.