

NanoSpeed™ Ultra-Fast 1x1, 1x2, 2X2 Fiber Optical Switch



(9ns rise/fall time, 1Mhz, polarization insensitive, all wavelengths, bidirectional, up to 20W)

DATASHEET

[Return to the Webpage](#)



Features

- Low Loss
- High Reliability
- High Power
- Bidirectional

Applications

- Laser System
- Quantum System
- Instruments



Note: The specifications provided are for general applications with a cost-effective approach. If you need to narrow or expand the tolerance, coverage, limit, or qualifications, please [click this [link](#)]:

The NS Ultra-Fast Series (NF) fiber optical switch is based on a patented electro-optical configuration featuring low optical loss, wide temperature operation, and polarization insensitivity. The NS fiber optical switch has ultra-high reliability and can continuously operate for over 25 years in a vibration environment (passed Telcordia and space qualifications). The switch is bidirectional and available with configurations of polarization-independent or polarization-maintain. The rise/fall time is intrinsically related to the crystal properties, and the repetition rate is associated with the driver. The NF Series switch is mounted on an electronic driver having a 5V TTL control signal SMA input and a DC power supplier. There are poor frequency response sections in which the on/off ratio does not meet the spec due to the device's mechanical resonances. The on/off ratio can be optimized for certain frequencies with requests.

The NS series switches respond to a control signal with any arbitrary timing with frequency from DC up to MHz. The switch is usually mounted on a tuned driver prior to shipping. The electrical power consumption is related to the repetition rate the switch is operated.

Specifications

Parameter		Min	Typical	Max	Unit
Insertion Loss ^[1]	1900~2200nm		1.6	2.8	dB
	1700~2300nm		0.8	1.8	
	1260~1650nm		0.6	1.2	
	960~1100nm		0.8	1.3	
	780~960nm		1.2	1.5	
	520~680nm		1.5	2.3	
Cross Talk On/Off Ratio ^[2]	Single Stage	16	18 ^[2]	25	dB
PDL (SMF Switch only)			0.15	0.3	dB
PMD (SMF Switch only)			0.1	0.3	ps
PER (PMF Switch only)		18	25		dB
IL Temperature Dependency			0.25	0.5	dB
Return Loss		45	50		dB
Electrical-Optical Delay				200	ns
Optical Rise Time (Single Stage only) ^[3]		5	8	10	ns
Optical Fall Time (Single Stage only) ^[3]		5	8	10	ns
Minimum Pulse Width			90		ns
Repetition Rate ^[4]		DC		1	MHz
Optic Power Handling ^[5]	Normal power version		0.3	0.5	W
	High power version		5	20	W
Operating Temperature ^[6]		-5		45	°C
Storage Temperature		-40		85	°C

Notes:

[1] Measured without connectors. Each connector adds 0.2 to 0.3dB

[2] ± 25 nm, The typical cross talk is measured at DC-20kHz and may be degraded at a higher repeat rate.

[3] It is defined as the time it takes for the signal to transition between 10% and 90% of its peak intensity. For wavelengths > 1550 nm, the response is slow due to the limitation of the current driver. At 2000 nm, the rise/fall time is about 20 nanoseconds.

[4] The driver is optimized at a repeat rate >500kHz. The specs exclude a few resonant frequency points. The performance can be optimized at other frequencies.

[5] The standard version is defined at 1310nm/1550nm. For the shorter wavelength, the handling is reduced see the graph. High power version has a fiber end beam expander, thus cost more

[6] The switches can be operated in a wider temperature range from as -10 to 70°C, but some performances such as on/off ratio will be degraded.

Warning: This is an OEM module designed for system integration. Do not touch the PCB by hand. The electrical static can kill the chips even without a power plug-in. Unpleasant electrical shock may also be felt. For laboratory use, please buy a Turnkey system.

Legal notices: All product information is believed to be accurate and is subject to change without notice. Information contained herein shall legally bind Agiltron only if it is specifically incorporated into the terms and conditions of a sales agreement. Some specific combinations of options may not be available. The user assumes all risks and liability whatsoever in connection with the use of a product or its application.

Rev 06/24/26

P +1 781-935-1200

E sales@agiltron.com

W www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice. Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.

NanoSpeed™ Ultra-Fast 1x1, 1x2, 2X2 Fiber Optical Switch




(9ns rise/fall time, 1Mhz, polarization insensitive, all wavelengths, bidirectional, up to 20W)


DATASHEET

Mechanical Dimensions (Unit: mm)

Package A Available for normal power 1x1, 1x2 (SM), 2x2 (SM) selected wavelength




Package B For all power, all wavelength SM, PM 1x1, 1x2




Packaged with driver

NFPSW 1X1 2X2 & 1M driver



NFPSW 1X2 & 1M driver



*Product dimensions may change without notice. This is sometimes required for non-standard specifications.

+1 781-935-1200

sales@agiltron.com

www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice. Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.

DATASHEET


NanoSpeed™ Ultra-Fast 1x1, 1x2, 2X2 Fiber Optical Switch




(9ns rise/fall time, 1Mhz, polarization insensitive, all wavelengths, bidirectional, up to 20W)

DATASHEET


Typical Rise and Fall Optical Switching Profile (5ns)



Typical Optical Switching Repetition Profile (1MHz)



Typical Switching Response (optical delay ~150ns)



+1 781-935-1200

sales@agiltron.com

www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice. Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.

NanoSpeed™ Ultra-Fast 1x1, 1x2, 2X2 Fiber Optical Switch



(9ns rise/fall time, 1Mhz, polarization insensitive, all wavelengths, bidirectional, up to 20W)

DATASHEET

Ordering Information (Part Number)

Prefix	Type	Wavelength ^[1]	Configuration	Repetition Rate	Fiber Type	Fiber Cover	Fiber Length	Connector ^{[5][7]}	Optical Power ^[6]	Benchtop
NFSW-	1x1 = 11 1x2 = 12 2x2 ^[2] = 22	1060nm = 1 2000nm = 2 1310nm = 3 1480nm = 4 1550nm = 5 1625nm = 6 1750nm = A 780nm = 7 850nm = 8 650nm = E 550nm = F 450nm = G Special = 0	Single stage = 1 Single Stage 5W = H Special = 0	900kHz = 6 1.5MHz ^[3] = 7	SMF-28 = 1 HI1060 = 2 HI780 = 3 PM1550 = 5 SM600 = 6 SM800 = 8 PM850 = A PM780 = B PM630 = C PM980 = 9 MM50/125 ^[4] = M SM400 = 4 SM450 = D HI980 = E SM1950 = F PM405 = G PM460 = H PM1950 = K Special = 0	Bare fiber = 1 900um tube = 3 Special = 0	0.25m = 1 0.5m = 2 1.0 m = 3 Special = 0	None = 1 FC/PC = 2 FC/APC = 3 ST/PC = 6 LC/PC = 7 LC/APC = A E2000 APC = 9 LC/UPC = U Special = 0	Regular = R 1W = 1 2W = 2 3W = 3 5W = 5 10W = A 15W = C 20W = D	None = 1 Benchtop = B

[1]. Red Wavelength Bands are special orders. They use special crystals.

[2]. Ultra-fast 2x2 is made by four pc of 1x2

[3]. Under development. Please call for availability.

[4]. For laser with mode fill ratio CPR <14

[5]. High-power connectors can ordered as special.

[6]. Only single stage is available for power >1W.


[7]. The default connector configuration uses fiber with 0.9 mm buffer protection. The connector cannot be installed directly onto bare fiber because the bare fiber is prone to damage during shipping. However, the connector can be assembled on bare fiber if a 3 cm protective loose tube is added for reinforcement. The customer may remove this protective tube after testing. The optical power handling of a standard connector is less than 0.5 W for SMF-28 fiber and decreases further for smaller-core fibers.

Red Color-marked is special order with a higher price and longer lead time.

Note:

- ☐ PM1550 fiber works well for 1310nm, PM1310 fiber choice costs extra
- ☐ Opaque – light is blocked without applying a voltage
- ☐ Transparent – light goes through without applying a voltage

Benchtop Box Mechanical Dimension



*Product dimensions may change without notice. This is sometimes required for non-standard specifications.

+1 781-935-1200

sales@agiltron.com

www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice. Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.


NanoSpeed™ Ultra-Fast 1x1, 1x2, 2X2 Fiber Optical Switch




(9ns rise/fall time, 1Mhz, polarization insensitive, all wavelengths, bidirectional, up to 20W)

DATASHEET

Optical Power Handling vs Wavelength For Single-Mode Fibers



Typical Wavelength Dependence Profile



Electrical Driving Specification

Control signal Input: 0-5V through SMA connector
Power supply in driver: 110-220 AC
Power Consumption in driver: <10W

Operation Manual

1. Connect a control signal to the SMA connector on the PCB.
2. Attach the accompanied power supply (typically a wall-pluggable unit).
3. The device should then function properly.

Note: Do not alter device factory settings.

P +1 781-935-1200

E sales@agiltron.com

W www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice.
Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.

NanoSpeed™ Ultra-Fast 1x1, 1x2, 2X2 Fiber Optical Switch



(9ns rise/fall time, 1Mhz, polarization insensitive, all wavelengths, bidirectional, up to 20W)

DATASHEET

Application Notes

Fiber Core Alignment

Note that the minimum attenuation for these devices depends on excellent core-to-core alignment when the connectors are mated. This is crucial for shorter wavelengths with smaller fiber core diameters that can increase the loss of many decibels above the specification if they are not perfectly aligned. Different vendors' connectors may not mate well with each other, especially for angled APC.

Fiber Cleanliness

Fibers with smaller core diameters ($<5\text{ }\mu\text{m}$) must be kept extremely clean, contamination at fiber-fiber interfaces, combined with the high optical power density, can lead to significant optical damage. This type of damage usually requires re-polishing or replacement of the connector.

Maximum Optical Input Power

Due to their small fiber core diameters for short wavelength and high photon energies, the damage thresholds for device is substantially reduced than the common 1550nm fiber. To avoid damage to the exposed fiber end faces and internal components, the optical input power should never exceed 20 mW for wavelengths shorter 650nm. We produce a special version to increase the handling by expanding the core side at the fiber ends.

P +1 781-935-1200

E sales@agiltron.com

W www.agiltron.com

Information contained herein is deemed to be reliable and accurate as of the issue date. We reserve the right to change the design or specifications at any time without notice.
Agiltron is a registered trademark of Optowares Corporation in the U.S. and other countries.